

CH1016-WX

10" Chassis Monitor 1366x768

- **Modular mechanical design provides flexible product configuration and easy maintenance**
- **Optional built-in touch screen for interactive applications**
- **Optional auto-brightness sensor offers application by day and night**
- **Optional with different frames (Open Frame, Chassis Mount, Panel Mount, Rack Mount)**



Specifications

Panel:	Cell Type / Glass Surface	TFT LCD / Black Anti-Glare, low reflection coating	
	Aspect Ratio / Size	Wide 16:9 / 10,1" viewable diagonal area	
	Active Area / Pixel Pitch	222.72 (H) x 125.28 (V) / 0.1629 (H) x 0.1629 (V) mm	
	Native Res. / Colors	1366 (H) x 768 (V) / 262 K	
	Brightness / Contrast	200 cd/m2 (typ) / 500:1	
	Response Time	< 16 ms	
	Viewing Angle	Horiz. 90° (-45° ~ + 45°), Vert. 50° (-30° ~ + 20°)	
	Light Source	LED Light Source, Long Life 35.000 hrs (typ)	
Input Sources:	Audio System	2W Speaker x 2	
Input Terminals:	1 x VGA (15 Pin Female D-SUB) 1x PC Audio (Stereo headphone Jack) 1 x DC Power Plug		
Convenient Features:	Auto Calibration, Back Light Adjustment, Plug & Play (VESA DDC/CI, DDC 2B) OSD Multi Languages, Wall Mount Ready (VESA 75 x 75 mm)		
Power:	External AC-to-12VDC power adapter with universal / Auto-Sensing, AC 90 to 260 V, 50 / 60 Hz		
Power cons.	Operation / Power	9 watt, < 1 watt (Support DPMS)	
Operating:	Temperature / Humidity	0°C ~ 50°C, 10% ~ 90% (no condensation)	
Storage:	Temperature / Humidity	-20°C ~ 60°C, 10% ~ 90% (no condensation)	
Dimensions:	Physical	WxHxD = see drawing	
	Carton	WxHxD = TBD	
Weight:	N.W. / G.W	2.0 kg / 3.0 kg	
Options:	Touch	Enhanced Panel	Others
	Resistive Touch Capacitive Touch	Other resolutions High Brightness Wide Temperature Sunlight Readable Protection Glass	Digital Signage Motion Sensor Light Sensor Auto-Dimming SV+AV, DVI, HDMI

Errors and omissions excepted

Full-size drawing available on request

